

KENWOOD

Listen to the Future



TK-7302 /8302

VHF/UHF Compact FM Mobile Radios

FleetSync[®]



GPS

Kenwood's new TK-7302/8302 delivers reliable mobile performance with **extra wideband coverage (UHF: 70MHz)** and such features as QT/DQT signaling, multiple scan functions and a voice inversion scrambler. Yet this tough **IP54/MIL-STD-compliant radio** is decidedly user-friendly, providing high-quality audio, voice announcement, and a large display with adjustable brightness for simple operation, day and night.

16 CHANNELS, 2 ZONES

The TK-7302/8302 offers ample capacity for multiple channels and radio systems: 16 channels and 2 zones. And once it is programmed, users can select specific channels within a set range.

ENHANCED KENWOOD AUDIO

Clear audio means confident communications, but power output is not the only factor that determines how easy it is to use a radio in varying noisy environments. As an audio specialist experienced in psychoacoustics, Kenwood can draw on decades of expertise at every step: component selection, construction, optimization, evaluation and analysis. The resulting audio performance – specially engineered for transceivers and with frequency response optimized for the human voice – is undeniably clearer and crisper.

EXTERNAL D-SUB 15-PIN INTERFACE

A D-sub 15-pin terminal enables the simple connection of various types of external equipment. It can be used for Ignition sense, External Switch, Horn Alert, and External Mic, among others. A Molex interface is also available with the optional KCT-60M cable.



MULTIPLE SIGNALING

QT/DQT/DTMF

Encoder/decoder function uses QT/DQT to segregate talk groups, so users only hear calls from their own group. DTMF PTT ID is included for dispatch operations or for a simple remote control application.

FleetSync[®] PTT ID, SelCall & Status

Utilizing Kenwood's FleetSync[®] signaling protocol, the TK-7302/8302 has PTT ID (ANI: automatic number identification) and Selective Calling capabilities for managed dispatch operations. Programmed Status (by FPU) can also be sent.

2-tone (encode/decode)

The 2-tone signaling format is provided for use with the most common radio systems.

MDC-1200 signaling

Built-in MDC signaling means the following features are available:

- PTT ID Encode
- Emergency Encode
- Stun/Revive Decode
- Radio Check Decode

Emergency alert


For hazardous/hostile duty environments, a PF key can be programmed for emergency use to alert the dispatcher or other group members via DTMF, FleetSync[®] or MDC-1200 signaling.

PROGRAMMABLE VOICE INVERSION SCRAMBLER^{*1}

The built-in programmable voice inversion scrambler provides basic protection against casual eavesdropping. It is possible to have a unique scrambler setting for each channel by picking the voice inversion frequency from one of 16 tables.

PROGRAMMABLE BLUE LED

The blue LED indicator can be customized to provide useful status information. For example, it can be used in combination with the orange LED for Selective Call differentiation.



GPS FEATURE

Connected to an external GPS receiver, the TK-7302/8302 can transmit accurate vehicle location data to the central base station for fleet management purposes. Designated scrambler and GPS modules can be installed internally.

OTHER FEATURES

- Multiple Scan Functions, including Priority Scan
- Voting (automatic repeater search & selection)
- Independent Setting Per Channel (compander, scrambler)
- BCL (Busy Channel Lockout)
- 9 Programmable Function Keys
- Talk Around
- Horn Alert Function
- Companded Audio (narrow/wide)
- 3-colour LED (red, orange, green)
- Voice Announcement (choice of language between English, Spanish, French, German, Italian, Dutch, Russian and Chinese)
- Password Protection
- Time-out Timer
- Minimum Volume Setting (by FPU)
- Operator Selectable Tone Settings
- Embedded Message
- 8 Programmable Accessory Ports (for external control)
- Scan Del/Add Function
- Kenwood ESN (Electronic Serial Number)
- Radio Stun
- Adjustable Microphone Gain (FPU only): High/Normal
- Microsoft Windows[®] PC Programming & Tuning

^{*1} This function cannot be used in certain countries. Please contact your Kenwood dealer for further information.



Options

■ **KMC-35**
Microphone



■ **KMC-9C**
Desktop Microphone



■ **KMC-36**
Keypad Microphone



■ **KCT-18**
Ignition Sense Cable
(requires KCT-60 option)



■ **KMC-30**
Microphone



■ **KCT-36**
3m Extension Cable
(for KCT-60)



■ **KMC-32**
16-key Keypad
Microphone



■ **KCT-60**
Connection Cable



All accessories and options may not be available in all markets. Contact an authorized Kenwood dealer for details and complete list of all accessories and options.

Specifications

| | TK-7302 | TK-8302 |
|---|------------------------------------|------------------------------------|
| GENERAL | | |
| Frequency Range | | |
| Type 1 | 136-174 MHz | 450-520 MHz |
| Type 2 | - | 400-470 MHz |
| Number of Channels | | |
| Zone | 2 | 2 |
| Channel | Max.16 | Max.16 |
| Channel Spacing | 12.5 kHz / 25 kHz | 12.5 kHz / 25 kHz |
| Operating Voltage | 13.6 V DC±15 % | 13.6 V DC±15 % |
| Current Drain | | |
| Standby | 0.4 A | 0.4 A |
| Receive | 1.0 A | 1.0 A |
| Transmit | 8.0 A | 8.0 A |
| Operating Temperature Range | -22 °F ~ +140 °F (-30 °C ~ +60 °C) | -22 °F ~ +140 °F (-30 °C ~ +60 °C) |
| Frequency Stability | ±2.5 ppm (-22 °F ~ +140 °F) | ±2.5 ppm (-22 °F ~ +140 °F) |
| Antenna Impedance | 50 Ω | 50 Ω |
| Dimensions (W x H x D), Projections not included | 160 mm x 43 mm x 137 mm | 160 mm x 43 mm x 137 mm |
| Weight (net) | 1.18 kg | 1.18 kg |

Kenwood reserves the right to change specifications and features without prior notice.
FleetSync® is a trademark of Kenwood Corporation.
Windows® is a registered trademark of Microsoft Corporation in the United States and other countries.

| | TK-7302 | TK-8302 |
|--|-----------------------------------|-----------------------------------|
| RECEIVER (Measurements made per EIA/TIA-603) | | |
| Sensitivity (12dB SINAD) | | |
| Wide | 0.28 μV | 0.28 μV |
| Narrow | 0.35 μV | 0.35 μV |
| Selectivity | | |
| Wide | 75 dB | 75 dB |
| Narrow | 65 dB | 65 dB |
| Intermodulation Distortion | | |
| Wide | 70 dB | 70 dB |
| Narrow | 60 dB | 60 dB |
| Spurious Response | 75 dB | 75 dB |
| Audio Output (4 Ω impedance) | 4 W with less than 5 % distortion | 4 W with less than 5 % distortion |
| TRANSMITTER (Measurements made per EIA/TIA-603) | | |
| RF Output Power | 5 W ~ 25 W | 5 W ~ 25 W |
| Spurious Response | 70 dB | 70 dB |
| Type of Emission | | |
| Wide | 16K0F3E | 16K0F3E |
| Narrow | 11K0F3E | 11K0F3E |
| FM Hum & Noise | | |
| Wide | 45 dB | 45 dB |
| Narrow | 40 dB | 40 dB |
| Microphone Impedance | 600 Ω | 600 Ω |
| Audio Distortion | | |
| Wide | 3 % | 3 % |
| Narrow | 5 % | 5 % |

Applicable MIL-STD & IP

| Standard | MIL 810C Methods/Procedures | MIL 810D Methods/Procedures | MIL 810E Methods/Procedures | MIL 810F Methods/Procedures |
|------------------------|---------------------------------|--------------------------------|--------------------------------|--------------------------------|
| Low Pressure | 500.1 / Procedure I | 500.2 / Procedure I, II | 500.3 / Procedure I, II | 500.4 / Procedure I, II |
| High Temperature | 501.1 / Procedure I, II | 501.2 / Procedure I, II | 501.3 / Procedure I, II | 501.4 / Procedure I, II |
| Low Temperature | 502.1 / Procedure I | 502.2 / Procedure I, II | 502.3 / Procedure I, II | 502.4 / Procedure I, II |
| Temperature Shock | 503.1 / Procedure I | 503.2 / Procedure I | 503.3 / Procedure I | 503.4 / Procedure I, II |
| Solar Radiation | 505.1 / Procedure I | 505.2 / Procedure I | 505.3 / Procedure I | 505.4 / Procedure I |
| Rain* ² | 506.1 / Procedure I, II | 506.2 / Procedure I, II | 506.3 / Procedure I, II | 506.4 / Procedure I, III |
| Humidity | 507.1 / Procedure I, II | 507.2 / Procedure II, III | 507.3 / Procedure II, III | 507.4 |
| Salt Fog* ² | 509.1 / Procedure I | 509.2 / Procedure I | 509.3 / Procedure I | 509.4 |
| Dust* ² | 510.1 / Procedure I | 510.2 / Procedure I | 510.3 / Procedure I | 510.4 / Procedure I, III |
| Vibration | 514.2 / Procedure VIII, X | 514.3 / Procedure I | 514.4 / Procedure I | 514.5 / Procedure I |
| Shock | 516.2 / Procedure I, II, III, V | 516.3 / Procedure I, IV, V | 516.4 / Procedure I, IV, V | 516.5 / Procedure I, IV, V |

International Protection Standard

Dust & Water Protection IP54*²

*²: Necessary conditions are: (1) KMC-35/36 microphone is connected; (2) cap is installed on speaker connector; (3) cover is installed on D-sub 15-pin connector; and (4) neither KCT cable nor SP cable is connected.

Listen to the Future

Kenwood has always connected with people through sound. Now we want to expand the world of sound in ways that only Kenwood can, listening to our customers and to the pulse of the coming age as we head toward a future of shared discovery, inspiration and enjoyment.

Kenwood Electronics Australia Pty. Ltd.

Website: www.kenwood.com.au
Contact: communications@kenwood.com.au
Office: 02-8879-2266
Fax: 02-8879-2233



ISO9001 Registered
Communications Equipment Division
Kenwood Corporation